

Shakespeare®

SHAKESPEARE 5218 VHF—Magnetic Mount Antenna



Shakespeare introduces the 5218 antenna.

The antenna whip is Stainless Steel and connected into a strong magnetic base for fast and easy attachment to magnet friendly surfaces.

You can set this up and dethatch easily as you require

Supplied with 4.6m cable and standard PL-259 connection, the 5218 is the perfect temporary vehicle antenna for VHF band

Registered in England No. 02452908 – VAT No. GB 531 6758 38
Enterprise Way – Fleetwood – Lancashire – England – FY7 8RY
Tel: +44 (0) 1253 858787 Fax: +44 (0) 1253 859595

e-mail: info@jardenuk.co.uk Web: www.vtronix-antennas.com www.shakespeare-marine.com

TECHNICAL DATA

Magnetic Base Antenna

5218

<u>ELECTRICAL</u>	
FREQUENCY	156-162MHz
POLAR RADIATION	Omni Directional
POLARISATION	Vertical
SECTIONS	1 section
VSWR	1.5:1 at 156.8MHz
BANDWIDTH	156—162Mhz
CABLE	4.6m of RG58
CONNECTOR	PL-259 Male
<u>MECHANICAL</u>	
ELEMENT	Stainless Steel Whip
MOUNTING	Heavy Duty Magnetic Base
LENGTH	0.5m

The above figures & dimensions are nominal